



REF. NO.	DESCRIPTION	QTY.	SIZE
1	Conduit, rigid galvanized	15'	100 Amp 1 1/2"
2	Conductor	As required	2 copper
	Optional	As required	1/0 AL
3	Conduit Strap	3	1 1/2"
4	Screw, lag	6	As required
5	Ground Conductor	8'	#4 copper
6	Bushing, bonding type	1	1 1/2"
7	Galvanized locknut	2	1 1/2"
8	Meter base	1	Furnished by Coop
9	Copperweld ground rod	1	Installed by Coop
10	Ground rod clamp	1	Installed by Coop
11	Weatherhead	1	1 1/2"
12	Conduit nipple	1	1 1/2"
13	Weatherproof disconnect	1	100 Amp
14	Breaker or fuse	1	100 Amp

- Secure meter base and disconnect firmly to back of pole by using 8 - 1 1/2" x 12 RH wood lag screws.
- Identify neutral at weatherhead by removing 1" or more of insulation.
- If aluminum conductor is used, apply corrosion inhibitor to all connections.
- All work shall be done in accordance to the national, state or local electric codes.
- Rigid galvanized steel is the only type of conduit that is acceptable.
- Approximately 3 feet of conductor will extend from the weatherhead.
- All conductor from the meter base to the service disconnect shall be in conduit.

100 AMP OVERHEAD TO OVERHEAD SERVICE LOOP ON A POLE

Date: 7/18/2009
 Drawn By: BGA
 DRAWING NAME: TCEC47